

www.midacbatteries.com




POWER LINE

STAND-BY AGM PowerLine BATTERIES

Valve regulated
lead acid batteries
with absorbed electrolyte





	NOMINAL VOLTAGE	RATED CAPACITY (20°C): 10 HRS TO 1,80 VPC	WEIGHT (Kg)	DIMENSIONI - DIMENSIONS MAX. mm		
				X	Y	H
12 AM 100 F 12 AM 125 F 12 AM 125 F	12 Volt	100 Ah	42	125	558	230
	12 Volt	125 Ah	51	125	558	270
	12 Volt	150 Ah	60	125	558	320

POWER FOR THE FUTURE:

The new Midac POWERLINE range of Standby Batteries is a prompt and reliable answer to any request of power back-up, either for Telecommunications, UPSs, and Power Generation or Distribution.

Top quality components, the accurate design, the high specific energy and the Lead Calcium Tin alloys give to the POWERLINE batteries the reliability of a proven technology and the characteristics of long life and high performances.

MIDAC FRONT POWER:

MIDAC FRONT POWER batteries are equipped with female front terminals for easy connection and check from the outside of the cabinet. Their compact design is ideal for installations both into cabinets and on stands. Connectors and pillars are protected against electrical contacts by insulating covers with inspection holes. All MIDAC FRONT POWER Batteries are office compatible and can be installed into sealed cabinets thanks to the Midac gas venting system (MGS) that limits gas concentration and risk of explosion.

- **LONG LIFE (>12 YEARS IN FLOATING AT 25°C)**
- **EASY INSTALLATION**
- **TOP OR FRONT TERMINALS**
- **FLAME ARRESTOR VENT**
- **COMPACT DESIGN – HIGH SPECIFIC ENERGY**
- **OFFICE COMPATIBILITY**
- **NO MAINTENANCE**
- **CASE AND LID IN FLAME RETARDANT ABS V-0 (UL 94, EN 60707)**

APPLICABLE STANDARDS:

EN/IEC 60896-21,22
BS 6290 part 4

EUROBAT GUIDE

12 years and longer - Long Life



MIDAC S.p.A.

VIA A.VOLTA, 2 - Z.I. - 37038 SOAVE (VERONA) - ITALIA
TEL. +39 045 61 32 1 32 - FAX +39 045 61 32 1 33
E-mail: midac@midacbatteries.com

MIDAC DEUTSCHLAND GMBH

INDUSTRIEGEBIET OBERE SURBACH - HEIDSTRASSE, 5
35625 RECHTENBACH - DEUTSCHLAND
TEL. +49-6441-679260 - FAX +49-6441-6792615
E-mail: midac.de@arcor.de

MIDAC FRANCE S.A.R.L.

Z.I. - ROUTE DE COLMAR - BP 70 - 68502 GUEBWILLER CEDEX
FRANCE
TEL. +33 03 89 622380 - FAX +33 03 89 622375
E-mail: midac.batteries@wanadoo.fr



MIDAC'S OPERATIVE UNIT IS CERTIFIED ACCORDING ISO 9001:2000, ISO 14001:2004, OHSAS 18001:2007, ISO/TS 16949:2002, SA 8000:2001